PM-100 POCKET MULTIMETER

TESTING | TROUBLESHOOTING | ACCURACY

Product Features:

Small and perfectly formed with all the basic measurement features you're likely to need, including fully automatic operation by default: the Pocket Multimeter (PM-100) from Tempo Communications is great additional to any toolbox.

Carry it everywhere.

Truly pocket sized, yet immensely useful and built to international safety standards, the PM-100 will easily become your go-to tool for quickly checking electrical supplies and basic continuity.

Supplied in a convenient zipper case, the only control on this Pocket Multimeter is a single push button that switches the unit on and off, and cycles through the various tests:

1. Powers up in "automatic mode"

- AC voltage
- DC voltage
- Resistance
- 2. Manual selection of each function
 - Continuity
 - Electric Field (EF) (voltage detector)
 - Volts AC
 - Volts DC
- 3. 6000 Count large digit LCD
 - Resistance
 - Frequency
 - Capacitance





CXR T: +33 (0) 237 62 87 90 www.cxr.com

contact @ cxr.com

Renewed Vision. Innovation Forward.

PM-100 POCKET MULTIMETER

SPECIFICATIONS:

Display:	6000-count LCD	
Polarity:	Automatic	
Display Update Rate:	5 per second	
Temperature Coefficient:	Nominal 0.15 x (specified accuracy) per °C below 18 °C or above 28 °C	
Intelligent Automatic Power Off:	After 3 minutes of inactivity (approximately)	
Noise Rejection:*	Common Mode Rejection Ratio: > 60 dB from 0 Hz to 60 Hz when measuring ACV	
	Common Mode Rejection Ratio: > 100 dB at 0 Hz, 50 Hz, and 60 Hz when measuring DCV	
	Normal Mode Rejection Ratio: > 30 dB at 50 Hz and 60 Hz when measuring DCV	
Operating Conditions:	Temperature: 0 °C to 40 °C (32 °F to 104 °F)	
Relative Humidity (non-condensing):	80% maximum for temperatures up to 31 °C (88 °F),	
	decreasing linearly to 50% maximum at 40 °C (104 °F)	
Altitude:	2000 m (6500') maximum	
Pollution Degree:	2	
Storage Conditions:	-20 °C to 60 °C (-4 °F to 140 °F), 0% to 80% relative humidity (non-condensing)	
Battery:	3 V standard button battery (IEC-CR2032; ANSI-NEDA-54004LC)	
Low Battery:	Below 2.4 VDC	
Overvoltage Protection:	450 VDC/VAC RMS, 50/60 Hz	
Measurement Categories:	Cat II, 450 V	
	Cat III, 300 V	

Noise rejection is the ability to reject unwanted signals, or noise.
Normal mode voltages are AC signals that can cause inaccurate DC measurements.

 NMRR (Normal Mode Rejection Ratio) is a measure of the ability to filter out these signals.
Common mode voltages are signals present at the COM and + input terminals, with respect to ground, that can cause digit rattle or offset in voltage measurements. CMRR (Common Mode Rejection Ratio) is a measure of the ability to filter out these signals.

ACCURACY:

FREQUENCY

Range	Accuracy	Specified at
10.00 Hz to 30.00 kHz	± (0.5% + 4d)	less than 20 V sine RMS

DCV			
Range	Accuracy		
6.000 V	± (0.5% + 0.003 V)		
60.00 V	± (1.0% + 0.05 V)		
450.0 V	± (1.2% + 0.5 V)		
RESISTANCE (AUTO V·Ω MODE)			
Range	Accuracy		
6.000 kΩ	± (1.2% + 0.006 kΩ)*		
60.00 kΩ	± (1.0% + 0.04 kΩ)		
600.0 kΩ	± (1.0% + 0.4 kΩ)		
6.000 ΜΩ	± (2.0% + 0.004 MΩ)		
CAPACITANCE			
Range	Accuracy		
100.0 nF	± (3.5% + 0.6 nF)		
1000 nF	± (3.5% + 6 nF)		
10.00 µF	± (3.5% + 0.06 μF)		
100.0 µF	± (3.5% + 0.6 μF)		
ACV			
Range (50 to 60 Hz)	Accuracy		
6.000 V	± (1.5% + 0.005 V)		
60.00 V	± (1.5% + 0.05 V)		
450.0 V	± (1.5% + 0.5 V)		
WIRELESS ELECTRIC FIELD DETECTION (EF)			
Typical Voltage	Bar graph indication		
15 V to 55 V	-		
30 V to 85 V			
45 V to 145 V			



contact @ cxr.com



75 V to 190 V above 105 V

Renewed Vision. **Innovation** Forward.