



RACK-MEDIA16S

16 SLOTS UNIVERSAL MEDIA CONVERTER RACK WITH INTERNAL AC POWER



FEATURES

- Support 16 slots for FOC series Media Converters
- 19-inch Rack Mount, 2U height
- 3 Hot-swappable fans
- LED indication for Power supply
- Plug & Play Operation
- Small Form Factor Converter Chassis
- With fixed AC Power Installed

Introduction

RACK-MEDIA16S, Universal Media Converter Rack, provides 16 slots for any combination of FOC Media Converters.

Up to sixteen media converters can be powered by the Converter rack without the requirement of external power supplies.

More over, to acquire a convenient maintenance, 3 Hot-swappable fans can be changed while **RACK-MEDIA16S** is working.

All above user-friendly designs make **RACK-MEDIA16S** in a shape of high performance and reliability. **RACK-MEDIA16S** can be used as a table top unit or installed into a 19-inch rack by using 19-inch brackets shipped together with the unit.

Applications

Interface

Number of Module Slot: 16
Number of Fan: 3

LED

Power

Hot-Swappable

Fan

Power

Internal Power
AC 110V or 240V
Power Rated at 100W (Max)
DC 5V
Power Consumption: 9.5 W
(Empty Loading)

Typical Operation Temperature

Operation: 0° ~ 50° C
Storage Temperature: -20° ~ 60° C
Humidity: 5% ~ 90% non-condensing

Case material

Iron / Steel, Plastic

Dimension and Weight

440 x 285x 88 mm (WxDxH)
Shipping Weight: 6.8KG

Emission/Safety:

FCC Class A
CE
*For further reports, please contact us for update

Order Information

RACK-MEDIA16S Rack 19" 2U with on AC power and 3 FAN for 16 FOC-xxxx



CXR
T +33 (0) 237 62 87 90
www.cxr.com

17 Rue de l'Ornette 28410 Abondant France
contact@cxr.com